



Z-MD300A-AS Media Player

Let the perfect tunes elevate your mood
and takes you to deeper feelings.
The perfect media player for every vibes.



TOA's Z-MD300A-AS is a media player and digital processing FM radio tuner. The unit has a USB and SD Card slot that allows MP3 Playback and also has a Bluetooth function for receiving audio signals. The radio has the capability to store up to 30 channels. The unit can be mounted on a EIA equipment rack.



- 1U 19" rack type media player
- Play USB, SD/MMC Card, FM Radio, Bluetooth
- 3 stereo output terminals (Tuner Out, Priority Out, USB/SD Out)
- FM Radio with 30 preset stations and sleep timer
- Backlight
- Remote control



ideal for background music applications at retail, shopping malls, gym and fitness centers, clinic and medical centers, supermarkets

Specifications

Specification	Z-MD300A-AS
Power Source	24V DC; M3 Screw terminal or DC socket connector
Current Consumption	350mA
Frequency Response	20 - 20,000Hz , ±3 dB
Tuner Receiving Frequency	87.5 - 108MHz (50kHz step)
Audio Input	USB Port for memory stick (up to 32GB, Type file : MP3 file) SD Card slot (up to 32GB, Type file : MP3 file) FM antenna terminals Bluetooth
Audio Output	RCA audio output L and R channels for PRIORITY RCA audio output L and R channels for TUNER RCA audio output L and R channels for USB/SD/BLUETOOTH
Control Input	Play track 1-3, Play all, Stop : No- voltage make contact input, open voltage : 24V DC Short circuit current : Under 5mA, Removable terminal block
Channels of memory Tuner	30 Channels in total for FM broadcasts
Indicators	LCD Display Light Blue 3 LED Indicator Light Green
Operation Temperature	0°C to +40°C
Operation Humidity	Under 90% RH (no condensation)
Finish	Front Panel : Aluminum, Black, Anodize Case: Steel Plate, Black , Painting
Dimensions	482(W) x 44(H) x 229.5(D) mm
Weight	2.1kg
Accessories	Remote Control ...1, Antenna FM Radio ...1, Removable Terminal Plug (2 pins) ...1, Removable Terminal Plug (3pins)...2



Scan for more info



Specifications are subject to change without notice.